

INSTRUMENTATION ENGINEERING

Section A
**Sensors and
Industrial Instrumentation**
Section B
Optical Instrumentation



Comprehensive Theory
with Solved Examples and Practice Questions





MADE EASY Publications Pvt. Ltd.

Corporate Office: 44-A/4, Kalu Sarai (Near Hauz Khas Metro Station), New Delhi-110016 | **Ph. :** 9021300500

Email : infomep@madeeasy.in | **Web :** www.madeeasypublications.org

Section A : Sensors and Industrial Instrumentation

Section B : Optical Instrumentation

Copyright © by MADE EASY Publications Pvt. Ltd.

All rights are reserved. No part of this publication may be reproduced, stored in or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photo-copying, recording or otherwise), without the prior written permission of the above mentioned publisher of this book.



MADE EASY Publications Pvt. Ltd. has taken due care in collecting the data and providing the solutions, before publishing this book. In spite of this, if any inaccuracy or printing error occurs then **MADE EASY Publications Pvt. Ltd.** owes no responsibility. We will be grateful if you could point out any such error. Your suggestions will be appreciated.

EDITIONS

First Edition : 2019

Second Edition : 2020

Third Edition : 2021

Fourth Edition : 2022

Fifth Edition : 2023

Sixth Edition : 2024

CONTENTS

Sensors & Industrial Instrumentation + Optical Instrumentation

Sensors and Industrial IN : Section-A

CHAPTER 1

Introduction to Transducers 1-12

1.1	Transducers.....	1
1.2	Mechanical Transducers.....	1
1.3	Electrical Transducers.....	4
1.4	Characteristics of Transducers.....	7
1.5	Input Characteristics.....	10
1.6	Output Characteristics.....	10
	<i>Objective Brain Teasers</i>	12

CHAPTER 2

Resistive Transducers 13-37

2.1	Resistive Transducers.....	13
2.2	Strain Gauges.....	19
2.3	Null Mode.....	24
2.4	Resistance Thermometer (RTD).....	29
2.5	Thermistors.....	32
	<i>Objective Brain Teasers</i>	36

CHAPTER 3

Capacitive Transducers..... 38-51

3.1	Capacitive Transducers.....	38
3.2	Differential Arrangement.....	47
	<i>Objective Brain Teasers</i>	49

CHAPTER 4

Inductive Transducers..... 52-64

4.1	Inductive Transducers.....	52
4.2	Linear Variable Different Transformer (LVDT).....	53
	<i>Objective Brain Teasers</i>	63

CHAPTER 5

Piezoelectric Transducers 65-74

5.1	Piezoelectric Transducers.....	65
	<i>Objective Brain Teasers</i>	73

CHAPTER 6

Measurement of Flow 75-101

6.1	Measurement of Flow.....	75
6.2	Variable Head Flow Meters.....	76
6.3	Variable Area and Variable Head Flowmeters (Weirs and Flumes).....	85
6.4	Variable Area Type Flowmeters.....	87
6.5	Electromagnetic Flowmeters.....	90
6.6	Turbine Flowmeter.....	92
6.7	Vortex Meters.....	94
6.8	Ultrasonic Flowmeters.....	94
	<i>Objective Brain Teasers</i>	99

CHAPTER 7

Measurement of Pressure..... 102-123

7.1	Measurement of Pressure.....	102
7.2	Measurement of Pressure using Elastic Sensing Elements.....	104
7.3	Manometers.....	104
7.4	Manometric Fluid.....	105
7.5	Well Type Manometer.....	107
7.6	Inclined Tube Manometer.....	108
7.7	Ring Balance Manometer.....	110
7.8	Knudsen Gauge.....	116
7.9	Thermal Conductivity Gauges.....	118
	<i>Objective Brain Teasers</i>	123

CHAPTER 8**Measurement of Temperature..... 124-141**

- 8.1 Measurement of Temperature 124
- 8.2 Thermistor 125
- 8.3 Thermocouples..... 125
- 8.4 Various Connections of Thermocouples 130
- 8.5 Measurement of High Temperature..... 138
- Objective Brain Teasers* 139

CHAPTER 9**Measurement of Force..... 142-151**

- 9.1 Measurement of Force 142
- 9.2 Direct Measurement of Force..... 147
- Objective Brain Teasers* 151

CHAPTER 10**Measurement of Torque 152-158**

- 10.1 Measurement of Torque 152
- 10.2 Inductance Torque Transducer..... 156
- 10.3 Magneto-Strictive Transducers..... 157
- Objective Brain Teasers* 158

CHAPTER 11**Vibrations and Shock 159-164**

- 11.1 Vibrations and Shock..... 159
- 11.2 Accelerometers..... 160
- 11.3 Displacement Mode Working of Seismic Transducer ... 162
- Objective Brain Teasers* 164

CHAPTER 12**Measurement of Liquid Level 165-170**

- 12.1 Measurement of Liquid Level..... 165
- 12.2 Measurement of Liquid Level with Gamma Rays... 168
- Objective Brain Teasers* 169

CHAPTER 13**Measurement of Velocity..... 171-177**

- 13.1 Measurement of Velocity 171
- Objective Brain Teasers* 177

CHAPTER 14**Measurement of Viscosity 178-184**

- 14.1 Viscosity..... 178
- Objective Brain Teasers* 184

CHAPTER 15**Measurement of pH Value 185-189**

- 15.1 Measurement of pH Value 185
- Objective Brain Teasers* 189

CHAPTER 16**4-20 mA Two-wire Transmitter 190-194**

- 16.1 Introduction..... 190

Optical Instrumentation : Section-B**CHAPTER 1****Basic Optics 195-203**

- 1.1 Basic Optics 195
- 1.2 Reflection..... 195
- 1.3 Refraction 196
- 1.4 Snell's Law..... 196
- 1.5 Brewster's Law..... 199
- 1.6 Reflection Loss 200
- 1.7 Critical Angle 201
- Objective Brain Teasers* 202

CHAPTER 2

Fiber Optics	204-220
2.1 Fiber Optics	204
2.2 Numerical Aperture	205
2.3 Based on R.I.....	209
2.4 Based on Mode.....	210
2.5 Characteristics of Optical Communications.....	212
2.6 Modewise Comparison.....	216
2.7 Materialwise Comparison	216
<i>Objective Brain Teasers</i>	218

CHAPTER 3

Lasers	221-233
3.1 Lasers.....	221
3.2 Principle of Laser	221
3.3 Directionality.....	223
3.4 Intensity.....	225
3.5 Monochromaticity.....	225
3.6 Coherence	226
3.7 Spatial Coherence.....	227
3.8 Temporal Coherence	227
3.9 Gas Laser	228
3.10 Semiconductor Diode Laser	228
3.11 Solid Lasers.....	228
3.12 He-Ne Laser.....	228
<i>Objective Brain Teasers</i>	231

CHAPTER 4

Light Emitting Diode (LED)	234-237
4.1 Light Emitting Diode (LED).....	234
<i>Objective Brain Teasers</i>	237

CHAPTER 5

Photodiode	238-243
5.1 Photodiode	238
5.2 Sensitivity	238
<i>Objective Brain Teasers</i>	243

CHAPTER 6

Photoresistor	244-246
6.1 Photo-Resistor.....	244
6.2 Dark Resistance	244
6.3 Sensitivity	245
<i>Objective Brain Teasers</i>	246

CHAPTER 7

Interference	247-261
7.1 Interference.....	247
7.2 Interferometer.....	248
7.3 Metrology	255
<i>Objective Brain Teasers</i>	260

CHAPTER 8

Mass Spectrometer and UV-Vis Spectrophotometer	262-264
8.1 Mass Spectrometer	262
8.2 UV-Vis Spectrophotometer	263


■■■■

Introduction to Transducers

Section-A

1.1 TRANSDUCERS

A transducer is a device which converts one kind of energy to the other. The conversion can be to or from electrical, electromechanical, photonic, photo-voltaic or any other form of energy. Transducers are called as the primary sensing elements. They have a vast application in the industrial measurement and control. Industry handles a large number of process which include the measurement of different process variable like flow, temperature, pressure, liquid level etc., these process variables can easily be transduced or converted in the electrical form with the help of the electrical transducers, these electrical signals which are proportional to the process variables can then be used for display and the control purposes, and the input to the transducer is termed as the information. Transducers can be of mechanical or electrical type.




1.2 MECHANICAL TRANSDUCERS

These are the transducers which convert the mechanical quantity (e.g. force or torque) into the equivalent displacement. Some of the commonly used mechanical sensing elements are :

Spring Device

These are the mechanical transducers which convert a force or torque into displacement; These type of devices include.


Cantilever



When a force ' F ' is applied to a cantilever beam it gets bent to some displacement ' x ', the value of ' x ' can be easily find and is calibrated in terms of input force applied. So knowing about the displacement ' x ' we can easily find the amount of force applied to the cantilever beam.

Helical Spring


In case of Helical spring when a force ' F ' is applied to both the sides of the spring then a displacement ' x ' produced in the spring which is calibrated in terms of the applied force. So if we know about the displacement ' x ' we can easily determine the applied force ' F '.



Helical Spring

Torsion Bars


These type of transducers are used for the measurement of torque. The torsion bars are fixed to the shaft for torque measurement. When torque is produced, it produces an angular deflection/displacement into the bar, this angular displacement (θ) is proportional to the torque of the shaft.



Torsion Bar

Proving Rings


These type of transducers are used for the measurement of weight, force or load. The lateral outward force ' F ' is applied to the proving ring which causes the deflection ' x ' as shown in the given figure. The deflection ' x ' is calibrated in terms of the force ' F ' and hence can be used for the measurement of force. Proving rings are made of steel.



Proving Ring

Load Cell

Load cells are used for the measurement of force. They utilize the elastic members as the primary sensing element. The strain is produced in the load cells when an external force ' F ' as shown in the figure is applied to them. This strain is then sensed with the help of strain gauges. The strain measured is proportional to the applied force.




Load Cell

Pressure Sensitive Devices

Pressure sensitive devices are those devices which convert the applied pressure into the displacement. The displacement is then measured with the help of the electrical transducers. The output of the electrical transducers is proportional to the displacement and hence gives the measure of applied pressure. These can be of different types:

Bourdon Tube

Bourdon tube is a C-shaped tube which has two ends, with one end free (which is closed) and the other end kept open through which the fluid is allowed to enter. When the fluid pressure is allowed to enter the tube, the free end of the tube tries to straighten out end hence leads to the displacement of the pointer attached to it. This displacement can be amplified will the help of gear and pinion arrangement.



Bourdon tubes are preferred for high pressure measurement, as they have good accuracy at high pressure.


- Bourdon tubes measure gauge pressure, they are made up of brass, phosphor, bronze, beryllium copper, and steel.
- C-type Bourdon tube have an arc of 250° and hence they are called as the C-shaped Bourdon tubes.
- C-type Bourdon tube have low output displacement hence they need amplification which is provided by the gear and pinion arrangement, but the backlash error comes in due to pressure of gear and pinion arrangement.
- Spiral and Helical type have high output displacement and hence they do not need any gear pinion arrangement for amplification also they are free from backlash error.

Accuracy order

Spiral type > Helical type > C-type


Diaphragm

- Diaphragm are the thin circular disc which is used for the measurement of pressure. The unknown pressure is applied to one of its ends, and it tends to expand towards the opposite side. The displacement produced is proportional to the applied pressure.
- This displacement (d_m) is proportional to the applied pressure (P), hence knowing about this displacement we can easily find the pressure applied.



Diaphragm are used for low pressure measurement.

Types of Diaphragm




- Corrugated type diaphragm has greater surface area hence its sensitivity is higher than the flat diaphragm

Order of sensitivity:


Corrugated type > Flat type

Bellows

- Bellows are the pressure sensing elements. They consists of cylindrical metal box with corrugated walls made of spring material like phosphor bronze, brass and steel. The walls are very thin with thickness of about 0.1 mm.
- As shown in the figure above, the pressure ' P ' is allowed to enter from the left side of the bellows, this tends to expand the bellows to the right side (as the right end is free), but the bellows material is springly by nature and hence it puts a backward force and tries to come back and results in a displacement ' x ', proportional to the applied pressure ' P '.
- If the input pressure is low then the spring material can provide sufficient backward force to control it, but if input pressure is high the displacement will go uncontrolled. Thus, **Bellows are used for low pressure measurement.**

**Capsules**

- Two diaphragm are joined to each other to form a capsule. Increasing the pressure into the capsule causes it to expand while decreasing its pressure causes it to contract, so the resultant displacement produced is an indication of the pressure applied.
- Since two diaphragm are attached to each other, hence the combined displacement produced is greater than that produced by the single diaphragm. Hence, **Sensitivity of capsule > Sensitivity of diaphragm.**

**EXAMPLE : 1.1**

A transducer converts

- (a) mechanical energy into electrical energy only
- (b) mechanical displacement into electrical signal only
- (c) one form of energy into another form of energy only
- (d) electrical energy into mechanical form only

Solution : (c)**1.3 ELECTRICAL TRANSDUCERS**

- The transducers which convert the mechanical quantity into electric energy are called as the electric transducers. The mechanical quantity to be measured is first converted into displacement which is then converted to the electric energy with the help of an electrical transducers.
 - ♦ **Primary Transducers**
Mechanical (pressure or force etc.) → Displacement

◆ **Secondary Transducers**

Displacement → Electric Energy

- The electrical output may be either, current, voltage or frequency.

Another name of transducer is pickup.

Advantages of Electrical Transducers Over Mechanical Transducers

- Mechanical transducers have frictional losses while electrical transducers are free from frictional losses.
- Electrical signals can be easily amplified while it is difficult to amplify mechanical output.
- Electrical signals can be easily transmitted from one place to another hence they have vast telemetry applications.
- Mechanical transducers have mass-inertia effects, which can be minimized by electrical transducers.
- Signal conditioning can be done with the electrical transducers output, which can be brought to a desired power level, but mechanical output cannot be signal conditioned.

Classification of Transducers


The transducers can be classified on the basis of

- Transduction form used.
- Primary and Secondary transducers.
- Active and Passive transducers.
- Digital and Analog transducers.
- Transducers and Inverse transducers.

Classification Based on Principle of Transduction


- On the basis of principle of transduction used they can be classified as resistive, inductive or capacitive transducers, the transduction depends on how they transduce the input quantity into the resistance, capacitance or inductance which can be measured by bridge or any other electronic circuitry.

Electrical Parameter and Class of Transducer	Principle of Operation and Nature of Device	Typical Application
	Passive Transducers (externally powered)	
1. Resistance		
Potentiometer device	Positioning of the slider by an external force varies the resistance in a potentiometer or a bridge circuit.	Pressure, displacement
Resistance strain gauge	Resistance of a wire or semiconductor is changed by elongation or compression due to externally applied stress.	Force, torque, displacement.
Pirani gauge or hot wire meter	Resistance of a heating element is varied by convection cooling of a stream of gas.	Gas flow, gas pressure.
Resistance thermometer	Resistance of pure metal wire with wire with a large positive temperature co-efficient of resistance varies with temperature.	Temperature, radiant heat



Non-Conformity Error

Nonconformity errors are those errors in which the experimentally obtained transfer function is different from the theoretically obtained transfer function.



Hysteresis Error

When the transducer is used again and again or used more frequently, then the output of the transducer at a particular instant become sensitive to the previous values of inputs together with the input at that instant, hence we may get different outputs for same magnitude of inputs applied this is called as the hysteresis error.

EXAMPLE : 1.2

In a transducer, the experimentally obtained transfer function is different from the theoretical transfer function, the errors result from this difference are called.

- (a) Zero errors
 - (b) Sensitivity errors
 - (c) Nonconformity errors
 - (d) Dynamic errors
- [GAIL-2010]

Solution : (c)

EXAMPLE : 1.3

In a transducer, the observed output deviates from the correct value by a constant factor the resulting error is called

- (a) Zero error
- (b) Sensitivity error
- (c) Nonconformity error
- (d) Hysteresis error

Solution : (b)

1.5 INPUT CHARACTERISTICS

The first and the necessary consideration is the type of input we are going to measure and also its operating range. So for the input characteristics the type and operating range should be taken into account. The input characteristics includes the input resistance of the transducer.

Loading Effects

When the transducer is brought in contact with the quantity to be measured, it extracts some power or energy from it, which is called as the loading. Ideally the loading the transducer should be zero, or the measuring device must not extract any energy from the quantity to be measured.

1.6 OUTPUT CHARACTERISTICS

- Output characteristics of a transducer includes its output resistance. Ideally the output resistance of the transducer must be kept zero in order to have no-loading effects. Practically it cannot be kept zero so it must be kept minimum.

The output characteristics determines the amount of power that can be transferred to the succeeding stages.

- Depending on the output impedance of the transducer and the input impedance of the succeeding stage, the transducer may act as a constant voltage source or a constant current source.

Case-I :

$$R_0 \ll R_L$$

$R_0 \rightarrow$ output resistance of the source.

$R_L \rightarrow$ load resistance.

$$I = \frac{E}{R_0 + R_L}$$

$$E_L = \frac{ER_L}{R_0 + R_L} = \frac{E}{1 + \frac{R_0}{R_L}}$$

when ($R_0 \ll R_L$) then R_0/R_L is negligible.

$$E_L = E$$



So, if $R_0 \ll R_L$ then the transducer will act as a constant voltage source.

If the output impedance is low compared to the forward impedance of the system, the transducer has the characteristics of the constant voltage source.

Case-II :

$$R_0 \gg R_L$$

$$I_L = \frac{IR_0}{R_0 + R_L} = \frac{I}{1 + \frac{R_L}{R_0}}$$





OBJECTIVE BRAIN TEASERS

- Q.1** Inverse transducers
- converts electrical energy to any other form of energy
 - converts electrical energy to light energy
 - converts mechanical displacement into electrical signal
 - converts electrical energy to mechanical form
- Q.2** Which of the following is an active transducer?
- strain gauge
 - selsyn
 - photovoltaic cell
 - photoemissive cell
- Q.3** Some of the functional building blocks of a measurement system are:
Primary Sensing Element (PSE)
Variable Conversion Element (VCE), or Transducer
Data Transmission Element (DTE)
Variable Manipulation Element (VME)
Data Presentation Element (DPE)
The correct sequential connection of the functional building blocks for an electronic pressure gauge will be
- PSE, VME, VCE, DPE, DTE
 - PSE, VCE, VME, DTE, DPE
 - DTE, DPE, VCE, PSE, VME
 - PSE, VCE, DTE, DPE, VME
- Q.4** The transducers which convert the physical quantity into the mechanical displacement are called
- Primary transducers
 - Secondary transducers
 - Tertiary transducers
 - Inverse transducers
- Q.5** The transducers which convert the mechanical displacement into the electrical form are called the
- Primary transducers
 - Secondary transducers
 - Tertiary transducers
 - Inverse transducers


ANSWERS KEY

1. (a) 2. (c) 3. (b) 4. (a) 5. (b)

HINTS & EXPLANATIONS

3. (b)

Functional elements of a measurement system are shown below:



Basic Optics

1.1 BASIC OPTICS


- Light or visible light is the portion of electromagnetic spectrum that is visible to human eye and is responsible for the sense of sight.
- Visible light has a wavelength in the range of about 380 or 400 nm to about 760 or 780 nm, with a frequency of 405 THz To 790 THz.

Speed of light in vacuum = 3×10^8 m/sec.

$$\text{Refractive index of a material} = \frac{\text{Speed of light in vacuum}}{\text{Speed of light in that medium}}$$

when a ray of light travelling in air or in any other medium strikes the surface of another medium then a part of light is reflected back into the same (that is travelling) medium and is called as the Reflected Ray.


While a part of it is refracted to the medium to which it strikes and is called as the Refracted Ray.



1.2 REFLECTION

- Bending of light in the same medium in which it is travelling, when it strikes the surface of some other medium is called as the Reflection of light.

AO = Incident light ray
OB = reflected light ray
 θ_i = incident angle
 θ_r = reflected angle




Law of Reflection

$$\angle\theta_i = \angle\theta_r$$



No. of images formed when two mirrors are inclined at an angle θ is:



$$n = \frac{360^\circ}{\angle\theta} - 1$$

n = number of images formed.

θ = angle between the two inclined mirrors.

1.3 REFRACTION

Bending of light into the medium to which it strikes is called as the Refraction of light.

AO = Incident ray


OB = Refracted ray

α = Angle of incidence

β = Angle of refraction

n_1 = RI of medium 1

n_2 = RI of medium 2



1.4 SNELL'S LAW


According to Snell's law

In figure (a)

$$n_1 \sin \alpha = n_2 \sin \beta$$

Conditions of Refraction

(i) Rarer to Denser medium:



When a ray of light travels from rarer to a denser medium it bends towards the normal.



OBJECTIVE BRAIN TEASERS

- Q.1** Light shows
 (a) wave like behaviour
 (b) particle like behaviour
 (c) both particle as well as wave like behaviour
 (d) none of these
- Q.2** Brewster's law can be expressed as
 (a) $\mu = \tan r$ (b) $\tan r = \frac{1}{\mu}$
 (c) $\mu = \tan i$ (d) $\tan i = \frac{1}{\mu}$
- Q.3** In a light wave the plane at right angles to the plane of vibration is called
 (a) vibrating plane (b) plane of polarization
 (c) polarized plane (d) all the these
- Q.4** The vibrations of the light rays
 (a) is parallel to the direction of propagation
 (b) is perpendicular to direction of propagation
 (c) some parallel and some perpendicular to the direction of propagation
 (d) none of these
- Q.5** The refractive index is
 (a) Velocity of light in vacuum \times Velocity of light in medium
 (b) $\frac{\text{Velocity of light in medium}}{\text{Velocity of light in vacuum}}$
 (c) $\frac{\text{Velocity of light in vacuum}}{\text{Velocity of light in medium}}$
 (d) None of these
- Q.6** When a light passes from a medium of refractive index n_1 to a medium of refractive index n_2 , the reflection loss at the boundary is expressed as
 (a) $n_1 + n_2$ (b) $n_1 - n_2$
 (c) $(n_1 - n_2)^2$ (d) $\left(\frac{n_1 - n_2}{n_1 + n_2}\right)^2$
- Q.7** The refractive index of a material (varies with the wavelength as)
 (a) $\mu \propto \lambda$ (b) $\mu \propto \frac{1}{\lambda}$
 (c) $\mu \propto \lambda^2$ (d) $\mu \propto \frac{1}{\lambda^2}$
- Q.8** A ray of light incident on a glass plate at an angle 60° . The reflected and refracted rays are found to be mutually perpendicular. The refractive index of glass is
 (a) 1.5 (b) 1.62
 (c) $\frac{2}{\sqrt{3}}$ (d) $\sqrt{3}$
- Q.9** Speed of light in air is 3×10^8 m/sec. What will be the speed of light in diamond. (Given R.I. of diamond is 2.4).
 (a) 3×10^8 m/sec (b) 322 m/sec
 (c) 1.25×10^8 m/sec (d) 7.2×10^8 m/sec
- Q.10** A ray of light is made to fall on a glass plate at an angle of 58° and the reflected ray is completely plane polarized. Find the angle of refraction
 (a) 58° (b) 28°
 (c) 38° (d) 32°
- Q.11** A ray of light is incident on the surface of a glass sheet of refractive index 1.55 at the polarizing angle. Calculate the angle of refraction
 (a) 36° (b) 38°
 (c) 33° (d) 42°
- Q.12** Find the time taken by light to travel a distance of 700 m in water. ($\mu_{\text{water}} = 4/3$)
 (a) 0.26 nsec (b) 0.36 nsec
 (c) 0.21 nsec (d) 0.31 nsec
- Q.13** A laser beam is made to pass through two separate tissues. Speed of light in tissue A is 2×10^5 m/sec. and in tissue B is 2.5×10^5 m/sec. If the length of both the tissues are same and equal to 2 m find the ratio of the refractive index of tissue B with respect to the tissue A.
 (a) 4/5 (b) 5/4
 (c) 8/5 (d) 5/8

ANSWERS KEY

1. (c) 2. (a) 3. (b) 4. (b) 5. (c)
6. (d) 7. (d) 8. (d) 9. (d) 10. (d)
11. (c) 12. (d) 13. (a)

HINTS & EXPLANATIONS

2. (a)

$$i = \tan^{-1} \mu = \tan^{-1} 1.55$$

$$i + r = 90^\circ$$

$$\therefore r = 90^\circ - 57.17 = 32.83^\circ$$

8. (d)

$$\mu = \tan^{-1} 60^\circ = \sqrt{3}$$

9. (d)

$$\frac{n_1}{n_2} = \frac{v_2}{v_1}$$

$$\therefore v_{\text{diamond}} = \frac{1}{24} \times 3 \times 10^8$$

$$= 1.25 \times 10^8 \text{ m/sec}$$

10. (d)

$$i + r = 90^\circ$$

$$\therefore r = 90^\circ - 58 = 32^\circ$$

11. (c)

$$i = \tan^{-1}(1.55) = 57.17^\circ$$

$$r = 90^\circ - 57.17^\circ = 32.8^\circ$$

12. (d)

$$V_{\text{water}} = \frac{3 \times 10^8}{4/3} = 2.25 \times 10^8 \text{ m/sec}$$

$$t = \frac{d}{V_{\text{water}}} = \frac{700}{2.25 \times 10^8}$$

$$= 0.31 \text{ nsec}$$

13. (a)

$$RI = \frac{\text{Velocity of light in air}}{\text{Velocity of light in the medium}}$$

$$\therefore RI \propto \frac{1}{\text{Velocity of light in medium}}$$

$$\frac{\mu_B}{\mu_A} = \frac{V_A}{V_B}$$

$$= \frac{2 \times 10^5}{2.5 \times 10^5} = \frac{20}{25} = \frac{4}{5}$$

